

20 M/C Questions

Name: _____

Important Instructions

1. Read all the instructions and both sides (back and front) of all pages.
2. Manage your time when answering questions on this test.
Answer the questions you know, first.

Multiple Choice - 20 Questions - 15 of 15%

(Office use only: 9 11 2 13 17 18 4 6 20 16 15 12 19 5 7 10 1 8 3 14)

1. Which is equivalent to: $(ab)'$
 - a. ab'
 - b. $a + b$
 - c. $a'b'$
 - d. $a' + b'$
 - e. $a'b$
2. Convert 46 decimal to octal (base 8):
 - a. **2E octal**
 - b. **38 octal**
 - c. **106 octal**
 - d. **56 octal**
 - e. **46 octal**
3. The BIOS ROM table for characters starts at **0xFFA6E**, and each character uses 8 bytes. Upper-case Z is ASCII code **0x5A**. Which is the ROM table address of this character?
 - a. **FFA6:02D0**
 - b. **FFAC:0008**
 - c. **FFD3:000E**
 - d. **FFA6:005A**
 - e. **FFA6:0068**
4. If you add one (1) to each 9-bit decimal number below, which addition will cause the *carry* flag to be set?
 - a. **510**
 - b. **255**
 - c. **511**
 - d. **256**
 - e. **257**

5. What are the smallest and largest decimal integers a 16-bit word can hold using two's complement representation?
 - a. **-65,536 65,535**
 - b. **-65,535 65,535**
 - c. **-32,768 32,767**
 - d. **-32,767 32,767**
 - e. **-32,767 32,768**
6. Express in hexadecimal the value stored in memory by:
char x = ~0x4
 - a. **FFFFB hexadecimal**
 - b. **F4 hexadecimal**
 - c. **FB hexadecimal**
 - d. **B hexadecimal**
 - e. **0B hexadecimal**
7. Given the MARIE instruction **JUMP 203** located at memory location **123h**, what is the value of the **PC** (a) *during* the actual execution of the instruction (from its location in the IR) and (b) *after* the instruction has finished executing?
 - a) **a) PC = 124h b) PC = 203h**
 - b) **a) PC = 123h b) PC = 203h**
 - c) **a) PC = 124h b) PC = 204h**
 - d) **a) PC = 203h b) PC = 123h**
 - e) **a) PC = 203h b) PC = 124h**
8. A small computer has an 18 bit word length. Like MARIE, all instructions are one word long and have an opcode part and a single-address part. The instruction set opcode has space for 48 different operations. Given the number of bits remaining after the opcode, what is the range of addresses possible in this small machine?
 - a. **0 to 2048**
 - b. **0 to 2047**
 - c. **0 to 4096**
 - d. **0 to 4095**
 - e. **0 to 1023**
9. If the number **0x12345678** is stored in memory on a little-endian computer, what value is stored in the lowest memory byte location?
 - a. **78**
 - b. **123**
 - c. **1**
 - d. **12**
 - e. **8**

10. How many different bit patterns (numbers) can be represented with 11 bits?

- a. 4096 patterns
- b. 2047 patterns
- c. 2048 patterns
- d. 22 patterns
- e. 1024 patterns

11. Convert 91 decimal to hexadecimal (base 16):

- a. 91 hex
- b. 145 hex
- c. 133 hex
- d. 511 hex
- e. 5B hex

12. If you add one (1) to each 9-bit decimal number below, which addition will cause the *overflow* flag to be set?

- a. 256
- b. 511
- c. 510
- d. 257
- e. 255

13. Express in hex the value stored in memory by:

```
char x = 0xAA | 0x77
```

- a. 77 hexadecimal
- b. AA77 hexadecimal
- c. 121 hexadecimal
- d. FF hexadecimal
- e. AA hexadecimal

14. The mnemonic for a MARIE opcode of '**4**' is **SUBT**. If the two-line MARIE program fragment "**SUBT FOO**" followed by "**FOO, HEX 2021**" is assembled and loaded into MARIE memory starting at location **724h**, what is the hexadecimal value of the memory at location **724h**:

- a. 7254 hexadecimal
- b. 2021 hexadecimal
- c. 2020 hexadecimal
- d. 4724 hexadecimal
- e. 4725 hexadecimal

15. ASCII upper-case **Z** is **0x5A**. Which of these is the ASCII code for lower-case **a**?

- a. 0x35
- b. 0x55
- c. 0x34
- d. 0x41
- e. 0x61

16. ASCII upper-case **Z** is **0x5A**. Represent this in eight bits using odd parity and give the result in hexadecimal:

- a. 0x5A
- b. 0x5B
- c. 0xDA
- d. 0x15A
- e. 0x05A

17. Which DEBUG segment/offset address is equivalent to **A000:1234**?

- a. A100:0234
- b. A120:3400
- c. A123:4000
- d. A120:0340
- e. A001:2340

18. Which is equivalent to: **(a' + b)'**

- a. **a'' + b'**
- b. **a'b**
- c. **a' + b'**
- d. **ab'**
- e. **a + b'**

19. Which DEBUG segment/offset address is equivalent to **E900:1234**?

- a. DD60:DC34
- b. E587:49C4
- c. E481:5B24
- d. DF10:C134
- e. DBEC:E384

20. In 16-bit two's complement representation, what decimal number do you get when you add one to decimal **32,767**:

- a. -32,768 decimal
- b. -32,767 decimal
- c. 0 decimal
- d. 32,768 decimal
- e. -1 decimal